

2 Channel Line Output Converter with Auto Remote Amplifier Turn-on

ALOC2

Connect line output converter gray wire(+) and gray/black wire(-) to the right speaker output of the source unit;

Connect line output converter white wire(+) and white/black wire(-) to the left speaker output of the source unit;

Connect line output converter yellow wire to vcc +12v;

Connect line output converter black wire to ground;

Connect line output converter blue wire to remote turn-on for amplifier;

If there is only one stereo minus, connect both line output converter minus wires to it;

The rca jacks are the output for the line output converter, 6:1 step down w/adjust control pots for the desired output;

